

Appendix 1 - Radvision XT5000 - Detailed physical information

Dimensions: (w x h x d) 29 x 16.5 x 4 cm

The XT5000 CODEC has a Kensington lock slot on the rear panel on the right hand side.

Video Inputs	<u>Signal Type</u>	<u>Connector</u>
Main camera	Digital	HDMI
PC input	Analogue RGB	DVI-I*
	Digital	

*The DVI-I input will auto detect the following signal formats:

- Analogue RGB
- Digital

Video Outputs	<u>Signal Type</u>	<u>Connector</u>
Main monitor	<u>Digital</u>	HDMI*
Second monitor	<u>Digital</u>	HDMI

Note: The Main Monitor HDMI* output includes embedded audio.

Audio Inputs	<u>Level</u>	<u>Connector</u>
Microphone 1	Microphone	RJ11

Aux Audio	Analog/ Digital	3.5mm Mini-jack
-----------	--------------------	-----------------

Audio Outputs	<u>Level</u>	<u>Connector</u>
Main output	Digital	HDMI
Main output stereo	Analog/ Digital	3.5mm Mini-jack

Data

1. 2 off LAN 10/100/1000 Mbits/s Ethernet connection (RJ45)
2. 2 off USB connector

Cables Supplied

Cables supplied were with demonstration systems so we could not comment on what is received with a new system.

Mobility

The XT5000 is small, portable and lightweight, it can be moved easily. To establish a connection, each new location will need the local area network information re-entered into the configuration menu.

Source URL: <https://community.jisc.ac.uk/library/appendix-1-radvision-xt5000-detailed-physical-information>